

Printer type			MONITOUCH type				Remarks	
Manufacturer	Model	Printer port	Interface	V9	TS2060	V8		
PR-201								
-	Any models compatible with MS-DOS and control codes of PC-PR201	Parallel	USB-A	✓	✓ *1	✓	*2	
		Serial	MJ1/MJ2		✓	✓	✓	
ESC-P								
SEIKO EPSON	LP-S280DN (Monochrome laser printer)	USB-B	USB-A	✓	-	-	V9 : OS Ver. 3.30 or later	
	VP-D500 (Dot impact printer)	Parallel	USB-A	-	✓ *1	✓	*2	
Serial		MJ1/MJ2		-	✓	✓		
-	Any models compatible with MS-DOS and control codes of ESC/P24-J84, ESC/P-J84, or ESC/P Super	Parallel	USB-A	✓	✓ *1	✓	*2	
		Serial	MJ1/MJ2	✓	✓	✓		
CBM-292/293								
CITIZEN SYSTEMS	CT-P292/293	Serial	MJ1/MJ2	✓	✓	✓	*3	
NADA ELECTRONICS	MPT-262F	Serial	MJ1/MJ2	✓	✓	✓	*3 *4	
	MP-192	Serial	MJ1/MJ2	✓	✓	✓	*3 *4	
MR-400								
SATO	M-48Pro8	Serial	MJ1/MJ2	✓	✓	✓	*5	
EPSON ESC/P-R (V9 series only)								
SEIKO EPSON	EP-979A3	USB-B	USB-A	✓	-	-		
		LAN	Ethernet	✓	-	-		
	EP-306 / XP-55	USB-B	USB-A	✓	-	-		
		LAN	Ethernet	✓	-	-		
	PX-049A	USB-B	USB-A	✓	-	-		
	PX-S160T	USB-B	USB-A	✓	-	-		
		LAN	Ethernet	✓	-	-		
	PX-S350	USB-B	USB-A	✓	-	-		
		LAN	Ethernet	✓	-	-		
	PX-S740	USB-B	USB-A	✓	-	-	V9 : OS Ver. 3.30 or later	
		LAN	Ethernet	✓	-	-	V9 : OS Ver. 3.30 or later	
	EP-712A	USB-B	USB-A	✓	-	-	V9 : OS Ver. 4.00 or later	
	HP HPLIP (V9 series only)							
	HP	Supporting HPLIP version up to 3.18.6	USB-B	USB-A	✓	-	-	V9 : Hardware Ver. f or later, OS Ver. 4.00 or later
LAN			Ethernet	✓	-	-	V9 : Hardware Ver. f or later, OS Ver. 4.00 or later	
PictBridge-compatible printer								
SEIKO EPSON	EP-306	USB-A	USB-B	✓	✓	✓		

*1: Connectable with TS2060i only. (TS2060 does not have a USB-A port.)

*2: Use a USB-parallel conversion cable, "UC-PGT" from ELECOM for parallel connection to USB-A.

*3: No printing of screen images

*4: Character graphics cannot be used for data sheet printing.

*5: Barcode printing only