

Printer type			MONITOUCH type				Remarks
Manufacturer	Model	Printer port	Interface	V9	TS2060	V8	
PR-201							
-	Any models compatible with MS-DOS and control codes of PC-PR201	Parallel	USB-A	✓	✓ *1	✓	*2
		Serial	MJ1/MJ2	✓	✓	✓	
ESC-P							
SEIKO EPSON	LP-S280DN (Monochrome laser printer)	USB-B	USB-A	✓	-	-	V9 : OS Ver. 3.30 or later
	VP-D500 (Dot impact printer)	Parallel	USB-A	-	✓ *1	✓	*2
		Serial	MJ1/MJ2	-	✓	✓	
	VP-880 (Dot impact printer)	Parallel	USB-A	✓	✓ *1	✓	*2
-	Any models compatible with MS-DOS and control codes of ESC/P24-J84, ESC/P-J84, or ESC/P Super	Parallel	USB-A	✓	✓ *1	✓	*2
		Serial	MJ1/MJ2	✓	✓	✓	
CBM-292/293							
CITIZEN SYSTEMS	CT-P292/293	Serial	MJ1/MJ2	✓	✓	✓	*3
NADA ELECTRONICS	MP262	Serial	MJ1/MJ2	✓	✓	✓	*3 *4
	MP192	Serial	MJ1/MJ2	✓	✓	✓	*3 *4
MR-400							
SATO	M-48Pro8	Serial	MJ1/MJ2	✓	✓	✓	*5
EPSON ESC/P-R (V9 series only)							
SEIKO EPSON	EP-979A3	USB-B	USB-A	✓	-	-	
		LAN	Ethernet	✓	-	-	
	EP-810A	USB-B	USB-A	✓	-	-	V9 : OS Ver. 3.30 or later
	EP-306	USB-B	USB-A	✓	-	-	
		LAN	Ethernet	✓	-	-	
	PX-049A	USB-B	USB-A	✓	-	-	
	PX-S160T	USB-B	USB-A	✓	-	-	
		LAN	Ethernet	✓	-	-	
	PX-S350	USB-B	USB-A	✓	-	-	
		LAN	Ethernet	✓	-	-	
	PX-S740	USB-B	USB-A	✓	-	-	V9 : OS Ver. 3.30 or later
		LAN	Ethernet	✓	-	-	V9 : OS Ver. 3.30 or later
	EW-M660FT	USB-B	USB-A	✓	-	-	V9 : OS Ver. 3.30 or later
	PictBridge-compatible printer						
SEIKO EPSON	EP-979A3	USB-A	USB-B	✓	✓	✓	V9 : OS Ver. 3.30 or later
	EP-810A	USB-A	USB-B	✓	✓	✓	V9 : OS Ver. 3.30 or later
	EP-880A	USB-A	USB-B	-	✓	✓	
	EP-306	USB-A	USB-B	✓	✓	✓	

*1: Connectable with TS2060i only. (TS2060 does not have a USB-A port.)

*2: Use a USB-parallel conversion cable, "UC-PGT" from ELECOM for parallel connection to USB-A.

*3: No printing of screen images

*4: Character graphics cannot be used for data sheet printing.

*5: Barcode printing only